



# ZX Spectrum cheat sheet

## Editing

CapsShift + Space	BREAK
CapsShift + 2	(K or L edit modes) CAPS LOCK
CapsShift + 0	(K or L edit modes) DELETE
0	(G edit mode) DELETE
CapsShift + 1	(K, L, or C edit modes) EDIT
CapsShift + 9	(K, L, or C edit modes) GRAPHICS
CapsShift + 3	(K, L, or C edit modes) TRUE VID
CapsShift + 4	(K, L, or C edit modes) INV VID
9	(E edit mode) BRIGHT
8	(E edit mode) UNBRIGHT

## Arrows

CapsShift + 5	(K, L, or C edit modes) Left
CapsShift + 6	(K, L, or C edit modes) Down
CapsShift + 7	(K, L, or C edit modes) Up
CapsShift + 8	(K, L, or C edit modes) Right

## Symbols

SymbolShift + N	(K, L, or C edit modes) ,
SymbolShift + M	(K, L, or C edit modes) .
SymbolShift + Z	(K, L, or C edit modes) :
SymbolShift + O	(K, L, or C edit modes) ;
SymbolShift + 1	(K, L, or C edit modes) !
SymbolShift + C	(K, L, or C edit modes) ?
SymbolShift + P	(K, L, or C edit modes) "
SymbolShift + 7	(K, L, or C edit modes) '
SymbolShift + 3	(K, L, or C edit modes) #
SymbolShift + 4	(K, L, or C edit modes) \$
SymbolShift + X	(K, L, or C edit modes) £
SymbolShift + 5	(K, L, or C edit modes) %
SymbolShift + 6	(K, L, or C edit modes) &
SymbolShift + 2	(K, L, or C edit modes) @
SymbolShift + P	(E edit mode) ©
SymbolShift + K	(K, L, or C edit modes) +
SymbolShift + J	(K, L, or C edit modes) -
SymbolShift + B	(K, L, or C edit modes) *

SymbolShift + V	(K, L, or C edit modes) /
SymbolShift + S	(E edit mode)
SymbolShift + D	(E edit mode) \
SymbolShift + 8	(K, L, or C edit modes) (
SymbolShift + 9	(K, L, or C edit modes) )
SymbolShift + Y	(E edit mode) [
SymbolShift + U	(E edit mode) ]
SymbolShift + F	(E edit mode) {
SymbolShift + G	(E edit mode) }
SymbolShift + R	(K, L, or C edit modes) <
SymbolShift + T	(K, L, or C edit modes) >
SymbolShift + L	(K, L, or C edit modes) =
SymbolShift + Q	(K, L, or C edit modes) <=
SymbolShift + E	(K, L, or C edit modes) >=
SymbolShift + W	(K, L, or C edit modes)
SymbolShift + H	(K, L, or C edit modes) ^
SymbolShift + 0	(K, L, or C edit modes) _
SymbolShift + A	(E edit mode) ~

## A

G	(E edit mode) ABS
SymbolShift + W	(E edit mode) ACS
SymbolShift + Y	(K, L or C edit modes) AND
SymbolShift + Q	(E edit mode) ASN
SymbolShift + I	(K, L or C edit modes) AT
SymbolShift + E	(E edit mode) ATN
SymbolShift + L	(E edit mode) ATTR

## B

SymbolShift + Z	(E edit mode) BEEP
B	(E edit mode) BIN
B	(K edit mode) BORDER
SymbolShift + B	(E edit mode) BRIGHT

## C

SymbolShift + 9	(E edit mode) CAT
U	(E edit mode) CHR\$
SymbolShift + H	(E edit mode) CIRCLE
X	(K edit mode) CLEAR

SymbolShift + 5	(E edit mode) CLOSE #
V	(K edit mode) CLS
I	(E edit mode) CODE
C	(K edit mode) CONTINUE
Z	(K edit mode) COPY
W	(E edit mode) COS

**D**

D	(E edit mode) DATA
SymbolShift + 1	(E edit mode) DEF FN
D	(K edit mode) DIM
W	(K edit mode) DRAW

**E**

SymbolShift + 7	(E edit mode) ERASE
X	(E edit mode) EXP

**F**

SymbolShift + V	(E edit mode) FLASH
SymbolShift + 2	(E edit mode) FN
F	(K edit mode) FOR
SymbolShift + 0	(E edit mode) FORMAT

**G**

H	(K edit mode) GO SUB
G	(K edit mode) GO TO

**I**

U	(K edit mode) IF
SymbolShift + I	(E edit mode) IN
SymbolShift + X	(E edit mode) INK
N	(E edit mode) INKEY\$
I	(K edit mode) INPUT
R	(E edit mode) INT
SymbolShift + M	(E edit mode) INVERSE

**L**

K	(E edit mode) LEN
L	(K edit mode) LET

SymbolShift + 3	(E edit mode) LINE
K	(K edit mode) LIST
V	(E edit mode) LLIST
Z	(E edit mode) LN
J	(K edit mode) LOAD
C	(E edit mode) LPRINT

**M**

T	(E edit mode) MERGE
6	(E edit mode) MOVE

**N**

A	(K edit mode) NEW
N	(K edit mode) NEXT
SymbolShift + S	(K, L or C edit modes) NOT

**O**

SymbolShift + 4	(E edit mode) OPEN #
SymbolShift + U	(K, L or C edit modes) OR
SymbolShift + O	(E edit mode) OUT
SymbolShift + N	(E edit mode) OVER

**P**

SymbolShift + C	(E edit mode) PAPER
M	(K edit mode) PAUSE
O	(E edit mode) PEEK
M	(E edit mode) PI
Q	(K edit mode) PLOT
SymbolShift + 8	(E edit mode) POINT
O	(K edit mode) POKE
P	(K edit mode) PRINT

**R**

T	(K edit mode) RANDOMIZE
A	(E edit mode) READ
E	(E edit mode) REM
S	(E edit mode) RESTORE
Y	(K edit mode) RETURN
T	(E edit mode) RND

R	(K edit mode) RUN
---	-------------------

## S

S	(K edit mode) SAVE
---	--------------------

SymbolShift + K	(E edit mode) SCREEN\$
-----------------	------------------------

F	(E edit mode) SGN
---	-------------------

Q	(E edit mode) SIN
---	-------------------

H	(E edit mode) SQR
---	-------------------

SymbolShift + D	(K, L or C edit modes) STEP
-----------------	-----------------------------

SymbolShift + A	(K, L or C edit modes) STOP
-----------------	-----------------------------

Y	(E edit mode) STR\$
---	---------------------

## T

P	(E edit mode) TAB
---	-------------------

E	(E edit mode) TAN
---	-------------------

SymbolShift + G	(K, L or C edit modes) THEN
-----------------	-----------------------------

SymbolShift + F	(K, L or C edit modes) TO
-----------------	---------------------------

## U

L	(E edit mode) USR
---	-------------------

## V

J	(E edit mode) VAL
---	-------------------

SymbolShift + J	(E edit mode) VAL\$
-----------------	---------------------

SymbolShift + R	(E edit mode) VERIFY
-----------------	----------------------

Via: slady.net

Last modification: 3/2/2021 9:17:19 □□□□□□□□

More information: [defkey.com/hi/sinclair-zx-spectrum-shortcuts](https://defkey.com/hi/sinclair-zx-spectrum-shortcuts)

[Customize this PDF...](#)