

Logitech G915 Lightspeed Wireless RGB cheat sheet

Connection

To pair the keyboard with another device over Bluetooth, hold the Bluetooth button on the keyboard for 3 seconds. The keyboard will become visible on other devices for pairing.

- When battery level is above 15%, it'll light momentarily when started.
- The indicator will pulse green when charging.

Last modification: 6/21/2021 3:39:17 PM

More information: defkey.com/logitech-g915-lightspeed-wireless-rgb-shortcuts

[Customize this PDF...](#)

Lighting functions

Brightness + 1	Colorwave (left to right)
Brightness + 2	Colorwave (right to left)
Brightness + 3	Colorwave (center out)
Brightness + 4	Colorwave (bottom up)
Brightness + 5	Color cycle
Brightness + 6	Ripple
Brightness + 7	Breathing
Brightness + 8 or Brightness + 9	User-stored lighting
Brightness + 0	Cyan blue
Brightness + -	Decrease effect speed
Brightness + +	Increase effect speed

User-stored effects are saved on the keyboard by the G Hub software.

Macro recording

To record a macro:

1. Press the MR key.
 2. Press G key.
 3. Now type keys to be recorded.
 4. Press the MR key.
- To record a second macro for the same G key, press M2 key and repeat steps above.
 - For a third macro, press M3 and repeat steps above.

Onboard memory

The M1, M2, and M3 keys store the profiles. Profiles can be saved by G Hub software. They can be recalled without G Hub software installed.

Battery indicator

- The battery indicator becomes red when the battery level is below 15%.